

Hidden multiphoton dynamics in the Heitler regime of resonance fluorescence

Yanfeng Li,^{1,2,3,*} Manman Wang,^{1,2,3,*} Chuanyu Zeng,^{1,2,3} Hanqing Liu,^{4,5} Haiqiao Ni,^{4,5}
Zhichuan Niu^{④,4,5} and Chengyong Hu^{1,†}

¹*Beijing Academy of Quantum Information Sciences, Beijing 100193, China*

²*Beijing National Laboratory for Condensed Matter Physics, Institute of Physics, Chinese Academy of Sciences, Beijing 100190, China*

³*University of Chinese Academy of Sciences, Beijing 100049, China*

⁴*Institute of Semiconductors, Chinese Academy of Sciences, Beijing 100083, China*

⁵*College of Materials Science and Opto-Electronic Technology, University of Chinese Academy of Sciences, Beijing 101408, China*



(Received 10 September 2025; accepted 12 December 2025; published 2 January 2026)

Resonance fluorescence from a two-level emitter is a standard route to single-photon generation, where the emitter produces only one photon at a time, and multiphoton emission or scattering is inherently suppressed. In this study, we challenge this paradigm in the weak-excitation limit, where coherent scattering dominates. Using a single quantum dot in a microcavity, we show that the incoherent component exhibits pronounced superbunching, revealing simultaneous multiphoton scattering from a single emitter. In contrast, the total reflected field—comprising the reflected driving field and incoherent scattering—displays perfect antibunching, arising from quantum interference that cancels two-photon probability amplitudes. By spectrally filtering the reflected field, we tune the relative contributions of coherent and incoherent components, observing transitions in photon statistics from antibunching to superbunching, or to Poissonian light. Supported by master-equation simulations and an interference-based model, these results uncover the hidden but fundamental role of multiphoton dynamics in resonance fluorescence, and open avenues for generating nonclassical light in cavity and waveguide quantum electrodynamics.

DOI: [10.1103/hgzx-twpk](https://doi.org/10.1103/hgzx-twpk)

I. INTRODUCTION

Resonance fluorescence (RF) [1,2] from a coherently driven two-level system (2LS) is a cornerstone of quantum optics, providing a paradigmatic platform for studying quantum light-matter interactions and generating nonclassical light [3]. Under resonant excitation, the emitted light comprises two distinct components: a coherent (elastic) part arising from Rayleigh scattering and an incoherent (inelastic) part originating from spontaneous emission. In the weak-driving regime, the RF is dominated by a narrow coherent peak that is phase locked to the excitation field [4]. As the driving strength increases, the RF becomes increasingly incoherent, producing Rabi oscillations in the time domain and the characteristic Mollow triplet in the frequency domain [5]. The incoherent spectrum is broadband, determined by the emitter's radiative lifetime. Across all regimes, RF exhibits strong photon antibunching, commonly interpreted as evidence that a 2LS emits one photon at a time.

While the physics of RF is well established in atomic systems [6–8], recent advances have renewed interest in its

implementation in solid-state quantum emitters [9], particularly semiconductor quantum dots (QDs) [10–12]. In the strong-driving regime, incoherent RF has been exploited to generate high-purity, indistinguishable single photons with high efficiency, representing a major step toward ideal solid-state single-photon sources [13–18]. In the weak-excitation limit, known as the Heitler regime [4], experiments have demonstrated single photons with subnatural linewidths [19–21] and shown that the observed antibunching arises from interference between coherent and incoherent components [22–24]. However, the photon statistics of the incoherent component alone have not been studied in this regime. Furthermore, spectral filtering [22,23] itself can introduce additional quantum noise that induces photon bunching [25], irrespective of photon-generation mechanisms. This raises the question of whether the observed antibunching stems from conventional single-photon emission or from more subtle multiphoton dynamics [26,27]. While such multiphoton dynamics have been investigated in the Mollow triplet under strong excitation [28,29], their behavior in the Heitler regime remains largely unexplored.

Here, we investigate photon correlations of the incoherent RF in the Heitler regime, using a single QD embedded in an optical microcavity operating in the Purcell regime. Our theoretical analysis predicts that the incoherent component exhibits superbunching, a signature of multiphoton scattering from a single emitter. We show that the observed antibunching in the total reflected field arises from interference between the driving field and multiphoton scattering, which suppresses

*These authors contributed equally to this work.

†Contact author: hucy@baqis.ac.cn

Published by the American Physical Society under the terms of the [Creative Commons Attribution 4.0 International](https://creativecommons.org/licenses/by/4.0/) license. Further distribution of this work must maintain attribution to the author(s) and the published article's title, journal citation, and DOI.

two-photon probability amplitudes. By spectrally filtering the reflected field, we tune the balance between the coherent and incoherent components and observe tunable transitions from antibunching to superbunching or Poissonian statistics. These findings, supported by master-equation simulations and an interference-based model, uncover the fundamental role of multiphoton dynamics in the Heitler regime and challenge the conventional picture of RF as a purely single-photon process.

II. MODELING PHOTON STATISTICS OF INCOHERENT RF

In contrast to single-sided cavity structures commonly used for emission-based single-photon sources [13–18], we employ a symmetric double-sided cavity [see Fig. 1(a)] resonantly coupled to a single QD in the Purcell regime. This design eliminates the need for cross-polarization filtering to suppress laser scattering. The system is characterized by a cooperativity $C = 2g^2/(\kappa\gamma_\perp) \gg 1$ and a critical photon number $n_0 = \gamma_\perp\gamma_\parallel/(4g^2) \ll 1$, where g is the QD-cavity interaction strength, κ is the cavity photon decay rate, $\gamma_\parallel$ is the QD spontaneous emission rate into noncavity modes, and $\gamma_\perp = \gamma_\parallel/2 + \gamma^*$ is the total decoherence rate, including the pure dephasing rate γ^* . This configuration realizes a one-dimensional atom, exhibiting cavity-enhanced RF and pronounced single-photon nonlinearity. Throughout this work, we characterize the driving strength using the normalized Rabi frequency $\Omega/\Gamma_\parallel$, where $\Gamma_\parallel = 4g^2/\kappa$ is the cavity-enhanced QD emission rate. We define the low-driving regime as $\Omega/\Gamma_\parallel < 1$, while the Heitler regime corresponds to the deep low-driving limit $S \ll 1$, with S the saturation parameter [see Eq. (B7) in Appendix B].

The cavity is driven resonantly by a coherent laser field with amplitude a_{in} [see Fig. 1(a)]. Using the input-output relation [30,31] [see Eq. (C1) in Appendix C], the field operators for the reflected and transmitted modes are expressed as

$$\begin{aligned}\hat{a}_r &= a_{\text{in}} + \sqrt{\kappa/2}\hat{a}, \\ \hat{a}_t &= \sqrt{\kappa/2}\hat{a},\end{aligned}\quad (1)$$

where $\hat{a}$ denotes the cavity field operator and $\kappa/2$ is the photon decay rate through each of the two symmetric cavity mirrors.

The reflected field can be expressed as the superposition of coherent and incoherent components, $\hat{a}_r = \langle \hat{a}_r \rangle + \delta \hat{a}_r$, where the mean field $\langle \hat{a}_r \rangle = a_{\text{in}} + \sqrt{\kappa/2}\langle \hat{a} \rangle$ produces a sharp spectral peak at the drive frequency, and the fluctuation term $\delta \hat{a}_r = \sqrt{\kappa/2}\delta \hat{a}$ accounts for quantum noise arising from spontaneous emission or inelastic scattering. Here, $\delta \hat{a} = \hat{a} - \langle \hat{a} \rangle$ with $\langle \delta \hat{a} \rangle = 0$ by definition. Similarly, the transmitted field is given by $\hat{a}_t = \sqrt{\kappa/2}\langle \hat{a} \rangle + \sqrt{\kappa/2}\delta \hat{a}$. Because the cavity is symmetric, the quantum fluctuation $\delta \hat{a}$ contributes equally to both reflected and transmitted fields.

Using the master-equation approach (see Appendix A), we calculate the second-order correlations of the reflected field, transmitted field, and the incoherent component, as shown in Figs. 1(b)–1(g). At low driving strengths, the reflected field shows antibunching, while the transmitted field and the incoherent component exhibit pronounced superbunching. As the driving strength increases, the zero-delay correlations of




FIG. 1. Calculated photon statistics of the reflected, transmitted, and incoherent fields. (a) Schematic of single-photon generation using a QD embedded in a symmetric double-sided microcavity operating in the Purcell regime. SNSPD, superconducting nanowire single-photon detector; BS, beam splitter. (b) Calculated second-order correlation function $g^{(2)}(\tau)$ of the reflected field at low driving strength ($\Omega = 0.14\Gamma_\parallel$). (c) Zero-delay correlation $g^{(2)}(0)$ of the reflected field as a function of driving strength. (d), (e) Same as (b), (c) but for the transmitted field. (f), (g) Same as (b), (c) but for the incoherent components of the transmitted and reflected fields. Solid curves in panels (b)–(g) are obtained from master-equation simulations; the dashed curve in panel (g) is calculated using Eq. (2) by modeling the QD-cavity system as an effective QD with a cavity-enhanced emission rate. Cavity-QED parameters used $g/2\pi = 4.7$ GHz, $\kappa/2\pi = 36.8$ GHz, $\gamma_\perp/2\pi = 0.18$ GHz, and $\gamma^* = 0$, as measured in Appendix E.

the reflected and transmitted fields evolve toward Poissonian statistics.

To gain further insight into the simulated results, we model the coupled QD-cavity system as an effective 2LS, which is valid in the low-driving regime where QD saturation remains weak. Owing to the fermionic nature of the 2LS operators $\sigma_\pm$, the total RF field exhibits perfect antibunching, with $g^{(2)}(0) = 0$. By decomposing $\sigma_\pm$ into coherent mean field and incoherent fluctuations, we derive an analytical expression for the zero-delay second-order correlation of the incoherent part (see Appendix B),

$$g_{\text{incoh}}^{(2)}(0) = \frac{I_{\text{coh}}^2 + 4I_{\text{coh}}I_{\text{incoh}}}{I_{\text{incoh}}^2} = \frac{1}{S^2} + \frac{4}{S}, \quad (2)$$

where I_{coh} , I_{incoh} denote the intensities of coherent and incoherent components of RF, respectively. The saturation parameter is defined as $S = I_{\text{incoh}}/I_{\text{coh}}$, which reduces to $S = 2(\Omega/\Gamma_{\parallel})^2$ at zero detuning [see Eq. (B7) in Appendix B].

Equation (2) implies that the incoherent RF exhibits strong superbunching ($g_{\text{incoh}}^{(2)}(0) \gg 1$) at low driving strengths ($S < 1$), in excellent agreement with master-equation simulations [Fig. 1(g)]. At strong driving strengths ($S \gg 1$), however, Eq. (2) predicts antibunching that deviates from the simulations, reflecting the breakdown of the effective 2LS approximation due to correlations between the QD and cavity operators. The superbunching of the incoherent RF reveals that even a single 2LS can scatter multiple photons in a correlated fashion, challenging the conventional view of RF as a strictly single-photon process.

At zero detuning, the transmitted field is dominated by the incoherent component of RF, since the coherent contribution vanishes in the low-drive limit [see Fig. 6 in Appendix A]. The transmitted field therefore inherits the superbunching of the incoherent scattering. This behavior can be qualitatively understood through a single-photon switching mechanism [32]—photon-induced tunneling [33,34]—enabled by the QD's saturation nonlinearity: An initially reflected photon saturates the QD over the interaction time (the exciton lifetime), allowing subsequent photons arriving within this lifetime to transmit. As a result, the reflected field becomes antibunched, whereas the transmitted field contains multiphoton events and exhibits bunching. This mechanism also applies to single atoms in free space. The observed photon bunching is consistent with theoretical predictions [35–37] and recent experiments [38–43]. Notably, Javadi *et al.* [38] measured $g^{(2)}(0) = 1.08$ for transmitted light in the low-drive regime, and Antoniadis *et al.* [40] reported $g^{(2)}(0) = 101$ after removing the coherent component in a chiral single-photon diode, both in strong agreement with our simulations.

Following the seminal work of Dalibard and Reynaud [26], the two-photon incoherent scattering process can be viewed as spontaneous four-wave mixing [Fig. 2(a)], in which two pump photons scatter into signal and idler photons at a rate proportional to the square of the driving power [see Eq. (B7) in Appendix B]. The corresponding three-photon incoherent scattering process is shown in Fig. 2(b).

We next demonstrate experimentally that the incoherent component of RF exhibits pronounced superbunching in the Heitler regime ($S \ll 1$), and that its interference with the reflected driving field suppresses the two-photon probability amplitude, giving rise to antibunching of the total reflected field. In contrast, the transmitted field, dominated by the incoherent component under the same conditions, exhibits strong superbunching.

III. INTERFERENCE MODEL FOR ANTIBUNCHING OF RF

We fabricate a micropillar cavity embedding a single QD, as illustrated in Fig. 3(a). The device operates in the Purcell regime with a cooperativity of $C = 6.9$ and a critical photon number of $n_0 = 6.9 \times 10^{-4}$. Details of the sample growth, fabrication process, and extracted cavity quantum electrodynamics (QEDs) parameters g , κ , and $\gamma_{\parallel}$ are provided in




FIG. 2. Multiphoton incoherent scattering processes in the Heitler regime of resonance fluorescence [26]. (a) Two-photon incoherent scattering, where two pump photons are converted into correlated signal and idler photons. (b) Three-photon incoherent scattering involves the correlated emission of three photons.

Appendix E. The cavity is engineered to suppress background reflection, yielding near-zero reflectivity ($R = 0.89\%$) at the fundamental cavity resonance under strong driving [Fig. 3(b), bottom trace]. By tuning the temperature, we bring the QD exciton transition into resonance with the cavity mode and observe a reflectivity peak of $R_{\text{QD}} = 46.6\%$ under weak driving [Fig. 3(b), top trace], which diminishes under strong driving due to QD saturation.

Photon statistics of the reflected field are measured without polarization filtering, as shown in Fig. 1(a). At zero detuning ($\Delta = 0$) and low driving strength ($\Omega = 0.11\Gamma_{\parallel}$), we measure a second-order correlation $g^{(2)}(0) = 0.030 \pm 0.002$ [Fig. 3(c)], demonstrating high single-photon purity. This value can be further improved by deconvolving the detector timing jitter. The dependence of $g^{(2)}(0)$ on driving strength at zero detuning is shown in Fig. 3(d), in good agreement with the simulated curve in Fig. 1(c).

In the Heitler regime ($S \ll 1$), the coherent component of the reflected field can be represented by a coherent state $|\alpha\rangle = |0\rangle + \alpha|1\rangle + (\alpha^2/\sqrt{2})|2\rangle$, where $\alpha < 1$ and the phase of the driving field defines the reference. The cavity-enhanced QD emission rate into the reflection channel, $\Gamma_{\parallel}/2$, sets a natural timescale $2/\Gamma_{\parallel}$ for defining the average photon number of the reflected field. By relating the coherent-state photon flux to the coherently reflected intensity, $\alpha^2\Gamma_{\parallel}/2 = I_{\text{coh}}$, we obtain $\alpha^2 = 2I_{\text{coh}}/\Gamma_{\parallel}$, where $I_{\text{coh}} = R_{\text{QD}}a_{\text{in}}^2$ and R_{QD} is the QD-induced coherent reflectivity. For simplicity, we assume




FIG. 3. Single-photon characteristics of the reflected field. (a) Scanning electron microscope image of the device. (b) Reflection spectra measured by scanning the driving laser frequency at different driving strengths. (c) Measured second-order correlation $g^{(2)}(\tau)$ (red curve) of the reflected field at low driving strength ($\Omega = 0.11\Gamma_{||}$), yielding $g^{(2)}(0) = 0.030 \pm 0.002$. The blue curve shows the result of master-equation simulations (see Appendix A). (d) Measured zero-delay correlation $g^{(2)}(0)$ of the reflected field as a function of driving strength.

a unit beam cross-sectional area and express the driving field intensity in units of photons per second. According to Eq. (B7) in Appendix B, we have $\alpha^2 = S$.

In the same regime, Fock states with $n \geq 3$ can be neglected, and the incoherent part of the reflected field is well approximated by a two-photon state $|\phi\rangle = |0\rangle + (\xi/\sqrt{2})|2\rangle$. The amplitude ξ is determined by the incoherent intensity through $\xi^2 = 2I_{\text{incoh}}/\Gamma_{||}$.

From Eq. (B7) in Appendix B, the incoherent intensity scales quadratically with the coherent part, $I_{\text{incoh}} = 2(I_{\text{coh}})^2/\Gamma_{||}$, which gives $\xi = 2I_{\text{coh}}/\Gamma_{||} = \alpha^2$. Consequently, the two-photon state exhibits superbunching with $g^{(2)}(0) = 1/\xi^2 = 1/S^2$, in agreement with Eq. (2) in the low-driving limit.

According to Eq. (1), the total reflected field can be expressed as a superposition $|\psi\rangle = |\alpha\rangle - |\phi\rangle$, where the minus sign reflects the phase shift π between the cavity field and the driving field [see Eq. (C3) in Appendix C]. Interference between these two contributions gives rise to a remarkable effect: The two-photon probability amplitude vanishes when $(\alpha^2 - \xi)/\sqrt{2} = 0$, leading to $g^{(2)}(0) = 0$ for the total reflected field. Such quantum interference, previously observed by mixing a coherent state with a weak two-photon state generated by spontaneous parametric down-conversion [44], here arises intrinsically from the interplay of coherent and incoherent components.

To capture the temporal dynamics, we express the two-photon wavefunction of the reflected field as

$$\psi^{(2)}(\tau) = \frac{\alpha^2}{\sqrt{2}} - \frac{\xi}{\sqrt{2}} e^{-\Gamma_{||}|\tau|}, \quad (3)$$

where the first term represents the constant two-photon amplitude of the coherent component and the second term accounts for the exponentially decaying contribution from the incoherent part [44]. Here, τ denotes the photon time delay. This yields the second-order correlation function

$$g^{(2)}(\tau) = \frac{(\alpha^2 - \xi e^{-\Gamma_{||}|\tau|})^2}{(\alpha^2 + \xi^2)^2}, \quad (4)$$

with normalization set by the total intensity. Since $\xi = \alpha^2 = S$, this model predicts $g^{(2)}(0) = 0$, reflecting perfect antibunching due to destructive interference between the two-photon amplitudes of coherent and incoherent components. Equation (4) also illustrates the strong sensitivity of $g^{(2)}(\tau)$ to their relative weights of these contributions.

To test this model, we perform two complementary experiments in which spectral filtering is used to modify the relative contributions of the coherent and incoherent components, allowing us to directly observe the resulting changes in the second-order correlation function.

IV. STATISTICS EVOLUTION BY VARYING THE COHERENT COMPONENT

In the first experiment, we selectively remove the coherent part of RF using a Fabry-Pérot filter and measure $g_F^{(2)}(\tau)$. The coherent component retains the narrow linewidth of the driving laser (below 100 kHz), while the incoherent component exhibits a broader spectral width $\Gamma_{||} = 2.8$ GHz, set by the cavity-enhanced QD exciton lifetime (see Appendix E). The Fabry-Pérot filter has a free spectral range of 20 GHz, a resolution of 31 MHz, and a peak transmission of $T_F = 63\%$. This allows spectral separation [see Fig. 4(a)]: The transmitted field contains only the coherent component, while the reflected field includes the full incoherent signal and a tunable fraction of the coherent component. The filter reflectivity for the coherent component is given by $R_F^{\text{coh}} = 1 - \alpha_F^{\text{coh}} - T_F^{\text{coh}}$, where $\alpha_F^{\text{coh}} = 21\%$ accounts for intrinsic losses and T_F^{coh} is the filter transmission for the coherent component. By tuning the filter resonance (see Fig. 8 in Appendix F), T_F^{coh} can be varied from 0% to 63%, corresponding to R_F^{coh} ranging from 79% to 16%, stabilized via active feedback.

The field passing through the filter exhibits Poissonian statistics [Fig. 4(b)] as expected for a coherent state, while the field reflected from the filter, which contains the entire incoherent component and varying amounts of coherent component, transitions from antibunching to superbunching as R_F^{coh} decreases. A maximum of $g_F^{(2)}(0) = 41 \pm 2$ is observed at $R_F^{\text{coh}} = 16\%$ [Fig. 4(c), red].

To model the filtered field, we modify the reflected field operator in Eq. (1) and define the filtered field as $\hat{a}_F = \sqrt{R_F^{\text{coh}}} \langle \hat{a}_r \rangle + \delta \hat{a}_r$. In the Heitler regime, the mean cavity field $\langle \hat{a} \rangle \simeq 0$ at zero detuning [see Eq. (C4) in Appendix C], so the filtered field operator can be simplified as $\hat{a}_F = \sqrt{R_F^{\text{coh}}} \hat{a}_{\text{in}} + \sqrt{\kappa/2} \hat{a}$. For $R_F^{\text{coh}} = 1$, $\hat{a}_F$ recovers the full reflected field $\hat{a}_r$, and for $R_F^{\text{coh}} = 0$, it reduces to the transmitted field $\hat{a}_t$. The second-order correlation function $g_F^{(2)}(\tau)$ is computed by the master equation (blue), showing excellent agreement with the experimental data (red) [Fig. 4(c)]. The simulations




FIG. 4. Photon statistics of RF under coherent-component filtering. (a) Experimental scheme using a Fabry-Pérot filter to spectrally separate the coherent and incoherent components of the reflected field from the QD-cavity system. BS1 and BS2, nonpolarizing beam splitters; APD, avalanche photodiode. (b) Measured second-order correlation $g_F^{(2)}(\tau)$ of the coherent component transmitted through the Fabry-Pérot filter. (c) Measured (red) and simulated (blue) $g_F^{(2)}(\tau)$ of filtered RF reflected from the Fabry-Pérot filter, for different reflectivities R_F^{coh} of the coherent component. $R_F^{\text{coh}} = 0$ corresponds to complete removal of the coherent part, while $R_F^{\text{coh}} = 1.0$ corresponds to the unfiltered RF. (d) Zero-delay correlation $g_F^{(2)}(0)$ as a function of R_F^{coh} for experiment (red symbols), master-equation simulations (blue symbols), and analytical calculations by Eq. (5) (solid line). The driving strength is fixed at $\Omega = 0.14\Gamma_{\parallel}$ in panels (b)–(d) corresponding to $\alpha^2 = \xi = 0.04$ for the unfiltered RF.

predict that $g_F^{(2)}(\tau)$ should approach zero at specific time delays; however, this behavior is not observed experimentally, likely due to spectral diffusion [45].

A heuristic expression for $g_F^{(2)}(\tau)$ is obtained by replacing α^2 with $R_F^{\text{coh}}\alpha^2$ in Eq. (4), yielding

$$g_F^{(2)}(\tau) = \frac{(R_F^{\text{coh}} - e^{-\Gamma_{\parallel}|\tau|})^2}{(R_F^{\text{coh}} + \xi)^2}. \quad (5)$$

Equation (5) accurately reproduces both the experimental and simulated results for $g_F^{(2)}(0)$, as shown in blue in Fig. 4(d).

V. STATISTICS EVOLUTION BY VARYING THE INCOHERENT COMPONENT

In the second experiment, we attenuate the incoherent part of RF by using spectral filters of varying bandwidths and measure the resulting $g_F^{(2)}(\tau)$. Three types of filters are used: a grating-based filter (8.7–9.4 GHz), a tilt-tunable Fabry-Pérot (0.69–4.7 GHz), and a high-resolution Fabry-Pérot (31 MHz). All filters fully transmit the narrowband coherent component ($T_F^{\text{coh}} = 1$), while selectively transmitting the broader incoherent spectrum. The transmission coefficient T_F^{incoh} for a Lorentzian filter as a function of its bandwidth Γ is shown in Fig. 5(b). As Γ increases, progressively more incoherent component is transmitted.

Figure 5(a) presents the evolution of $g_F^{(2)}(\tau)$ with decreasing T_F^{incoh} . As the incoherent component is suppressed, the




FIG. 5. Photon statistics of RF under incoherent-component filtering. (a) Measured (red) and calculated (blue) $g_F^{(2)}(\tau)$ of filtered RF transmitted through optical filters of varying bandwidths. (b) Calculated transmission of the incoherent component as a function of filter bandwidth. (c) Zero-delay correlation $g_F^{(2)}(0)$ vs filter bandwidth. Filled circles, experimental data; solid line, theoretical prediction from Eq. (6). The driving strength is kept at $\Omega = 0.14\Gamma_{\parallel}$, corresponding to $\alpha^2 = \xi = 0.04$ for the unfiltered RF.

antibunching dip weakens and broadens, approaching Poissonian statistics. This behavior is captured by replacing $\xi \rightarrow T_F^{\text{incoh}} \xi$ [see Eq. (G5) in Appendix G] and $\Gamma_{\parallel} \rightarrow \Gamma$ in Eq. (4), yielding

$$g_F^{(2)}(\tau) = \frac{(1 - T_F^{\text{incoh}} e^{-\Gamma|\tau|})^2}{[1 + (T_F^{\text{incoh}})^2 \xi]^2}. \quad (6)$$

This expression reproduces both the measured $g_F^{(2)}(\tau)$ and the zero-delay value $g_F^{(2)}(0)$, as shown in Figs. 5(a) and 5(c), and further explains the gradual evolution of the reflected-field statistics toward Poissonian behavior with increasing driving strength [Fig. 3(d)].

The results shown in Fig. 5(a) are identical to those reported in previous works [22,23], where the nature of the interference between the coherent and incoherent components was not addressed. The excellent agreement among the experimental, simulated, and analytical results confirms that the evolution of photon statistics in filtered resonance fluorescence originates from destructive quantum interference between a coherent state and a multiphoton state, which suppresses the two-photon probability amplitude and rules out filter-induced bunching effects [25].

VI. CONCLUSION AND OUTLOOK

We have shown that the incoherent component of resonance fluorescence from a single two-level emitter exhibits pronounced photon superbunching in the Heitler regime, revealing that multiphoton scattering arises even in systems conventionally regarded as single-photon sources. The total reflected field, however, displays perfect antibunching due to quantum interference between multiphoton incoherent scattering and the coherently reflected driving field, which suppresses the two-photon probability amplitude. By spectrally filtering the scatterings to adjust the relative weights of the coherent and incoherent components, we observe continuous transitions from antibunched to Poissonian and to superbunched photon statistics.

Master-equation simulations and the interference-based model introduced here reproduce these behaviors, showing that, in the weak-driving limit, two-photon processes are intrinsic to the system, while the apparent single-photon character emerges from destructive quantum interference. This interpretation may also extend to the strong-driving regime, where interference governs photon correlations across the Mollow triplet [28,29].

Beyond deepening the understanding of antibunching in resonance fluorescence, this work establishes a general framework for engineering photon correlations in cavity and waveguide QED. In particular, it provides a pathway for converting a Poissonian laser field into antibunched single photons that retain the laser's ultralong first-order coherence [32], offering promising applications for interference-based photonic quantum technologies [46,47], such as mode-pairing and asynchronous measurement-device-independent quantum key distribution developed recently [48–53] and single-photon-based quantum relays [54]. It further opens possibilities for realizing single-photon phased arrays and mode-locked single photons.

The tunability of photon statistics demonstrated here under continuous-wave excitation could be extended to weak pulsed operation by optimizing the cavity structure, cavity-QED parameters, and pulse temporal profiles. Further investigations along these directions are ongoing.

ACKNOWLEDGMENTS

We thank T. Shi for valuable discussions. C.H. acknowledges support from the Beijing Natural Science Foundation (Grant No. IS23069). Z.C.N. acknowledges support from the National Key Technology R&D Program of China (Grant No. 2018YFA0306101).

DATA AVAILABILITY

No data were created or analyzed in this study.

APPENDIX A: MODELING $g^{(2)}(\tau)$ OF INCOHERENT RF

The QD-cavity dynamics are governed by the master equation

$$\frac{d\rho}{dt} = -i[H_{\text{JC}}, \rho] + \frac{\kappa}{2}\mathcal{L}[\hat{a}]\rho + \frac{\gamma_{\parallel}}{2}\mathcal{L}[\hat{\sigma}_{-}]\rho + \frac{\gamma^{*}}{2}\mathcal{L}[\hat{\sigma}_{z}]\rho, \quad (\text{A1})$$

where ρ is the system density matrix, $\hat{a}$ is the cavity annihilation operator, $\hat{\sigma}_{\pm}$ are the QD raising and lowering operators, and $\mathcal{L}[\hat{O}]\rho = 2\hat{O}\rho\hat{O}^{\dagger} - \hat{O}^{\dagger}\hat{O}\rho - \rho\hat{O}^{\dagger}\hat{O}$ is the Lindblad superoperator. The driven Jaynes-Cummings Hamiltonian in the rotating frame of the driving field reads

$$H_{\text{JC}} = (\omega_c - \omega)\hat{a}^{\dagger}\hat{a} + (\omega_{\text{QD}} - \omega)\sigma_{+}\sigma_{-} + ig(\sigma_{+}\hat{a} - \hat{a}^{\dagger}\sigma_{-}) + i\sqrt{\kappa_1}a_{\text{in}}(\hat{a} - \hat{a}^{\dagger}), \quad (\text{A2})$$

where ω , ω_c , and ω_{QD} denote the frequencies of the driving field, cavity mode, and QD transition, respectively. g , $\gamma_{\perp}$, $\gamma_{\parallel}$, and γ^{*} are defined in the main text, and a_{in} is the driving field amplitude. The total cavity decay rate is $\kappa = \kappa_1 + \kappa_2 + \kappa_s$, where κ_1 and κ_2 are the output rates into reflection and transmission ports, and κ_s accounts for side losses. For the device studied, $\kappa_1 \simeq \kappa_2 + \kappa_s \simeq \kappa/2$. We restrict to the resonant case $\omega = \omega_c = \omega_{\text{QD}} = \omega_0$ in this work.

We solve the master equation numerically using the Quantum Optics Toolbox in Python (QuTiP) [55]. The steady-state coherent reflection and transmission coefficients are obtained by applying the input-output relations [30,31,56]:

$$r(\omega) = 1 + \sqrt{\kappa_1} \frac{\text{Tr}(\rho \hat{a})}{\langle a_{\text{in}} \rangle}, \quad t(\omega) = \sqrt{\kappa_2} \frac{\text{Tr}(\rho \hat{a})}{\langle a_{\text{in}} \rangle}. \quad (\text{A3})$$

The calculated results are shown in Fig. 6.

The second-order correlations are obtained via the quantum regression theorem. For the reflected and transmitted fields,

$$g_r^{(2)}(\tau) = \frac{\langle \hat{a}_r^{\dagger}(t) \hat{a}_r^{\dagger}(t + \tau) \hat{a}_r(t + \tau) \hat{a}_r(t) \rangle}{\langle \hat{a}_r^{\dagger}(t) \hat{a}_r(t) \rangle \langle \hat{a}_r^{\dagger}(t + \tau) \hat{a}_r(t + \tau) \rangle},$$

$$g_t^{(2)}(\tau) = \frac{\langle \hat{a}_t^{\dagger}(t) \hat{a}_t^{\dagger}(t + \tau) \hat{a}_t(t + \tau) \hat{a}_t(t) \rangle}{\langle \hat{a}_t^{\dagger}(t) \hat{a}_t(t) \rangle \langle \hat{a}_t^{\dagger}(t + \tau) \hat{a}_t(t + \tau) \rangle}, \quad (\text{A4})$$




FIG. 6. Calculated reflection and transmission in the low-driving regime. (a) Reflection spectra for the hot cavity (red, $g \neq 0$) and the cold cavity (black, $g = 0$). (b) Corresponding transmission spectra for the hot cavity (green) and cold cavity (black). The cavity-QED parameters are the same as in Fig. 1, with a side-leakage rate of 0.08κ .

where $\hat{a}_r$ and $\hat{a}_t$ are the reflected and transmitted field operators defined by Eq. (1).

To isolate the incoherent component, we decompose the cavity field as $\hat{a} = \langle \hat{a} \rangle + \delta \hat{a}$. The corresponding second-order correlation is then

$$g_{\text{incoh}}^{(2)}(\tau) = \frac{\langle \delta \hat{a}^\dagger(t) \delta \hat{a}^\dagger(t+\tau) \delta \hat{a}(t+\tau) \delta \hat{a}(t) \rangle}{\langle \delta \hat{a}^\dagger(t) \delta \hat{a}(t) \rangle \langle \delta \hat{a}^\dagger(t+\tau) \delta \hat{a}(t+\tau) \rangle}. \quad (\text{A5})$$

Because the reflected and transmitted fields are linear in $\hat{a}$, $g_{\text{incoh}}^{(2)}(\tau)$ are identical for the cavity, reflected, and transmitted fields.

APPENDIX B: ANALYTICAL EXPRESSION FOR $g^{(2)}(0)$ OF INCOHERENT RF

The zero-delay second-order correlation $g^{(2)}(0)$ of RF from a coherently driven 2LS is given by

$$g^{(2)}(0) = \frac{\langle \sigma_+^2 \sigma_-^2 \rangle}{\langle \sigma_+ \sigma_- \rangle^2}. \quad (\text{B1})$$

To separate coherent and incoherent contributions, we express the operators as $\sigma_+ = \langle \sigma_+ \rangle + \delta \sigma_+$ and $\sigma_- = \langle \sigma_- \rangle + \delta \sigma_-$ with $\langle \delta \sigma_\pm \rangle = 0$ by definition. The coherent and incoherent intensities are then given by $I_{\text{coh}} = \langle \sigma_+ \rangle \langle \sigma_- \rangle$ and $I_{\text{incoh}} = \langle \delta \sigma_+ \delta \sigma_- \rangle$, respectively. Substituting these into the unnormalized second-order correlation, we find

$$\begin{aligned} G^{(2)}(0) &= \langle \sigma_+^2 \sigma_-^2 \rangle \\ &= -\langle \sigma_+ \rangle^2 \langle \sigma_- \rangle^2 - 4\langle \sigma_+ \rangle \langle \sigma_- \rangle \langle \delta \sigma_+ \delta \sigma_- \rangle + \langle \delta \sigma_+^2 \delta \sigma_-^2 \rangle \\ &= -I_{\text{coh}}^2 - 4I_{\text{coh}}I_{\text{incoh}} + g_{\text{incoh}}^{(2)}(0)I_{\text{incoh}}^2, \end{aligned} \quad (\text{B2})$$

where the zero-delay correlation of the incoherent component is defined as

$$g_{\text{incoh}}^{(2)}(0) = \frac{\langle \delta \sigma_+^2 \delta \sigma_-^2 \rangle}{\langle \delta \sigma_+ \delta \sigma_- \rangle^2}. \quad (\text{B3})$$

In deriving Eq. (B2), we have used the operator identities: $\delta \sigma_\pm^2 = -\langle \sigma_\pm \rangle^2$, $\langle \delta \sigma_+ \delta \sigma_-^2 \rangle = -2\langle \sigma_- \rangle \langle \delta \sigma_+ \delta \sigma_- \rangle$, and $\langle \delta \sigma_+^2 \delta \sigma_- \rangle = -2\langle \sigma_+ \rangle \langle \delta \sigma_+ \delta \sigma_- \rangle$.

Owing to the fermionic nature of the 2LS operators, which satisfy $\sigma_\pm^2 = 0$, the total RF field is perfectly antibunched, i.e., $G^{(2)}(0) = 0$. Solving Eq. (B2) for the zero-delay correlation of

the incoherent component yields

$$g_{\text{incoh}}^{(2)}(0) = \frac{I_{\text{coh}}^2 + 4I_{\text{coh}}I_{\text{incoh}}}{I_{\text{incoh}}^2} = \frac{1}{S^2} + \frac{4}{S}, \quad (\text{B4})$$

where $S = I_{\text{incoh}}/I_{\text{coh}}$ is the saturation parameter. This expression indicates that the incoherent component exhibits strong superbunching in the low-driving limit ($S \ll 1$), and antibunching at strong driving strengths ($S \gg 1$).

To obtain analytical expressions for I_{incoh} and I_{coh} , we model the QD-cavity system as an effective 2LS. The optical Bloch equations yield the steady-state coherent and incoherent intensities at zero detuning as

$$\begin{aligned} I_{\text{coh}} &= \frac{\Gamma_{\parallel}}{2} \left[\frac{\Gamma_{\parallel}}{(\Gamma_{\parallel} + 2\gamma^*)} \frac{S}{(1+S)^2} \right], \\ I_{\text{incoh}} &= \frac{\Gamma_{\parallel}}{2} \left[\frac{\Gamma_{\parallel}S + 2\gamma^*(1+S)}{(\Gamma_{\parallel} + 2\gamma^*)} \frac{S}{(1+S)^2} \right], \end{aligned} \quad (\text{B5})$$

where the saturation parameter

$$S = \frac{(\frac{1}{2} + \frac{\gamma^*}{\Gamma_{\parallel}})\Omega^2}{(\omega_{\text{QD}} - \omega)^2 + (\frac{\Gamma_{\parallel}}{2} + \gamma^*)^2} \quad (\text{B6})$$

quantifies the degree of saturation of the QD transition and scales with the driving power.

Under resonant and transform-limited conditions ($\omega = \omega_{\text{QD}}$, $\gamma^* = 0$), Eqs. (B5) and (B6) reduce to

$$\begin{aligned} I_{\text{coh}} &= \frac{\Gamma_{\parallel}}{2} \left[\frac{S}{(1+S)^2} \right], \\ I_{\text{incoh}} &= \frac{\Gamma_{\parallel}}{2} \left[\frac{S^2}{(1+S)^2} \right] = SI_{\text{coh}}, \\ S &= 2 \left(\frac{\Omega}{\Gamma_{\parallel}} \right)^2. \end{aligned} \quad (\text{B7})$$

In the low-driving limit (i.e., Heitler regime, $S \ll 1$), the coherent and incoherent intensities scale linearly and quadratically with driving power, respectively, $I_{\text{coh}} = (\Gamma_{\parallel}/2)S$ and $I_{\text{incoh}} = (\Gamma_{\parallel}/2)S^2$.

APPENDIX C: PHASE SHIFT OF π BETWEEN DRIVING AND INTRACAVITY FIELDS

For the QD-cavity system in Fig. 1(a), the Heisenberg equations of motion for the cavity field operator $\hat{a}$ and the QD operators σ_- and σ_z , and the input-output relations [30,31] are

$$\begin{aligned} \frac{d\hat{a}}{dt} &= -\left[i(\omega_c - \omega) + \frac{\kappa}{2}\right]\hat{a} - g\sigma_- - \sqrt{\kappa_1}a_{\text{in}}, \\ \frac{d\sigma_-}{dt} &= -[i(\omega_{\text{QD}} - \omega) + \gamma_{\perp}]\sigma_- - g\sigma_z\hat{a} + F_{\sigma}(t), \\ \frac{d\sigma_z}{dt} &= 2g(\sigma_+\hat{a} + \hat{a}^\dagger\sigma_-) - \gamma_{\parallel}(1 + \sigma_z) + F_z(t), \\ \hat{a}_r &= a_{\text{in}} + \sqrt{\kappa_1}\hat{a}, \\ \hat{a}_t &= \sqrt{\kappa_2}\hat{a}. \end{aligned} \quad (\text{C1})$$

where all parameters are defined in Appendix A. The noise operators $F_{\sigma}(t)$ and $F_z(t)$ preserve the commutation relations.

In the low-driving limit ($S \ll 1$), the QD remains predominantly in its ground state, such that $\sigma_z \simeq -1$. In this regime, the steady-state cavity field satisfies

$$\langle \hat{a} \rangle = \frac{-\sqrt{\kappa_1} [i(\omega_{\text{QD}} - \omega) + \gamma_{\perp}] \langle a_{\text{in}} \rangle}{[i(\omega_{\text{QD}} - \omega) + \gamma_{\perp}] [i(\omega_c - \omega) + \frac{\kappa}{2}] + g^2}. \quad (\text{C2})$$

At zero detuning, this simplifies to

$$\langle \hat{a} \rangle = \frac{-\sqrt{\kappa_1} \gamma_{\perp} \langle a_{\text{in}} \rangle}{\frac{\kappa \gamma_{\perp}}{2} + g^2}, \quad (\text{C3})$$

revealing a phase shift of π between the reflected driving field and the intracavity field.

The steady-state coherent reflection and transmission coefficients at zero detuning are

$$\begin{aligned} r(\Delta = 0) &= \frac{\langle \hat{a}_r \rangle}{\langle a_{\text{in}} \rangle} = \frac{C}{1 + C}, \\ t(\Delta = 0) &= \frac{\langle \hat{a}_t \rangle}{\langle a_{\text{in}} \rangle} = -\frac{1}{1 + C}, \end{aligned} \quad (\text{C4})$$

where $C = 2g^2/(\kappa\gamma_{\perp})$ is the cooperativity and $\Delta = \omega - \omega_0$ is the detuning. In the high-cooperativity regime ($C \gg 1$), the QD-cavity system acts as a perfect mirror with $r(\Delta = 0) \simeq 1$ and $t(\Delta = 0) \simeq 0$.

APPENDIX D: SAMPLE GROWTH AND DEVICE FABRICATION

To realize an effectively symmetric double-sided cavity, the distributed Bragg reflectors (DBRs) were designed with intentional asymmetry such that leakage through the top mirror balances losses from the bottom mirror, sidewalls, and background absorption. The sample wafer was grown on semiinsulating (100) GaAs substrates via solid-source molecular beam epitaxy (Veeco Gen930). Low-density InAs QDs were formed via *in situ* annealing combined with an indium-gradient growth technique and embedded at the center of a λ -thick GaAs cavity ($\lambda = 920$ nm), sandwiched between 30 (bottom) and 18 (top) pairs of GaAs/Al_{0.9}Ga_{0.1}As DBR pairs. Circular pillar microcavities were fabricated using standard top-down nanofabrication. A 350-nm-thick SiO₂ hard mask was deposited via plasma-enhanced chemical vapor deposition and patterned into arrays of 2–3 μm diameter pillars using a DWL66+ maskless lithography system. The pattern was transferred into the semiconductor by chlorine-based inductively coupled plasma etching (PlasmaPro 100 Cobra 300, Oxford Instruments). Residual SiO₂ is removed in a final fluorine-based dry etching step to enhance the quality factor. Micropillars were chosen to host a single quantum dot resonantly coupled to the fundamental cavity mode, providing a high Purcell factor and negligible bare-cavity reflectivity at the mode center. The device studied here has a diameter of 2.4 μm .

APPENDIX E: QD EXCITON LIFETIME AND CAVITY-QED PARAMETERS

To determine the exciton lifetime and cavity-QED parameters, we measure the transient reflectivity when the QD is tuned into resonance with the cavity mode. A 5-ps




FIG. 7. QD exciton lifetimes measured on- and off-resonance with the cavity. On-resonance, extracted from reflected intensity; off-resonance, from resonance fluorescence at large detuning via temperature tuning.

mode-locked Ti:sapphire laser, stabilized at 80 MHz using a Lok-to-Clock module (Model 3930), provides the excitation. After deconvolving the instrument response function, the reflected signal exhibits a monoexponential decay (Fig. 7, green), yielding an on-resonance lifetime $\tau_{\text{on}} = 57$ ps, corresponding to a cavity-enhanced emission rate $\Gamma_{\parallel}/2\pi = 2.8$ GHz.

When the QD is detuned from the cavity by temperature tuning, the lifetime is obtained from RF measurements (Fig. 7, red), giving $\tau_{\text{off}} = 450$ ps, which corresponds to the emission rate into leaky modes, $\gamma_{\parallel}/2\pi = 0.35$ GHz.

From these lifetimes, we extract a Purcell factor $F_p = \tau_{\text{off}}/\tau_{\text{on}} - 1 = 6.9$. The cavity reflection spectrum shown in Fig. 3(b) yields a quality factor $Q = 8937$, corresponding to a cavity photon decay rate $\kappa/2\pi = 36.8$ GHz. Assuming the QD resides at a field antinode, we estimate the coupling strength as $g/2\pi = 4.7$ GHz using $F_p = 4g^2/(\kappa\gamma_{\parallel})$.

APPENDIX F: CHARACTERIZATION OF FABRY-PÉROT TRANSMISSION

We characterize the transmission spectrum of the high-resolution Fabry-Pérot filter (bandwidth 31 MHz) using a narrow-linewidth Ti:sapphire laser (<100 kHz over 100 μs).




FIG. 8. Transmission spectrum of the high-resolution Fabry-Pérot filter. The measurement shows a free spectral range of 20 GHz, a resolution (FWHM) of 31 MHz, and a peak transmission of $T_F = 63\%$. Inset: magnified view of a single transmission peak.

By varying the voltage applied to the piezo actuator, we tune the cavity resonance and record the transmission (see Fig. 8). This approach enables voltage-controlled adjustment of the transmission coefficient for narrowband signals, such as the driving laser or the coherent component of RF in this work.

APPENDIX G: TRANSFORMATION OF TWO-PHOTON STATE THROUGH A SPECTRAL FILTER

We consider a two-photon Fock state in the frequency domain,

$$|\psi^{(2)}\rangle = \frac{1}{\sqrt{2}} \iint d\omega_1 d\omega_2 \phi(\omega_1, \omega_2) \hat{a}^\dagger(\omega_1) \hat{a}^\dagger(\omega_2) |0\rangle, \quad (\text{G1})$$

where $\phi(\omega_1, \omega_2)$ is the joint spectral amplitude (JSA). $\hat{a}^\dagger(\omega)$ creates a photon at frequency ω .

A spectral filter with transmission function $T(\omega)$, e.g., a Lorentzian of bandwidth Γ , transforms the creation operator

according to

$$\hat{a}^\dagger(\omega) \rightarrow \sqrt{T(\omega)} \hat{a}^\dagger(\omega). \quad (\text{G2})$$

The filtered two-photon state is then

$$|\psi_F^{(2)}\rangle = \iint d\omega_1 d\omega_2 \sqrt{T(\omega_1)T(\omega_2)} \phi(\omega_1, \omega_2) \hat{a}^\dagger(\omega_1) \hat{a}^\dagger(\omega_2) |0\rangle, \quad (\text{G3})$$

which shows that the JSA transforms according to

$$\phi(\omega_1, \omega_2) \rightarrow \sqrt{T(\omega_1)T(\omega_2)} \phi(\omega_1, \omega_2). \quad (\text{G4})$$

In the degenerate case $\omega_1 = \omega_2 = \omega$, this reduces to

$$\phi(\omega, \omega) \rightarrow T(\omega) \phi(\omega, \omega). \quad (\text{G5})$$

This transformation is used to derive Eq. (6) from Eq. (4).

-
- [1] R. Loudon, *The Quantum Theory of Light* (Oxford University Press, Oxford, 2000).
 - [2] M. O. Scully and M. S. Zubairy, *Quantum Optics* (Cambridge University Press, Cambridge, 1997).
 - [3] H. J. Kimble, M. Dagenais, and L. Mandel, Photon antibunching in resonance fluorescence, *Phys. Rev. Lett.* **39**, 691 (1977).
 - [4] W. Heitler, *The Quantum Theory of Radiation* (Clarendon Press, Oxford, 1954).
 - [5] B. R. Mollow, Power spectrum of light scattered by two-level systems, *Phys. Rev.* **188**, 1969 (1969).
 - [6] C. N. Cohen-Tannoudji, Nobel lecture: Manipulating atoms with photons, *Rev. Mod. Phys.* **70**, 707 (1998).
 - [7] H. Walther, B. T. H. Varcoe, B.-G. Englert, and T. Becker, Cavity quantum electrodynamics, *Rep. Prog. Phys.* **69**, 1325 (2006).
 - [8] G. Wrigge, I. Gerhardt, J. Hwang, G. Zumofen, and V. Sandoghdar, Efficient coupling of photons to a single molecule and the observation of its resonance fluorescence, *Nat. Phys.* **4**, 60 (2008).
 - [9] O. Astafiev, A. M. Zagoskin, A. A. Abdumalikov, Yu. A. Pashkin, T. Yamamoto, K. Inomata, Y. Nakamura, and J. S. Tsai, Resonance fluorescence of a single artificial atom, *Science* **327**, 840 (2010).
 - [10] A. Muller, E. B. Flagg, P. Bianucci, X. Y. Wang, D. G. Deppe, W. Ma, J. Zhang, G. J. Salamo, M. Xiao, and C. K. Shih, Resonance fluorescence from a coherently driven semiconductor quantum dot in a cavity, *Phys. Rev. Lett.* **99**, 187402 (2007).
 - [11] E. B. Flagg, *et al.*, Resonantly driven coherent oscillations in a solid-state quantum emitter, *Nat. Phys.* **5**, 203 (2009).
 - [12] A. N. Vamivakas, Y. Zhao, C.-Y. Lu, and M. Atatüre, Spin-resolved quantum-dot resonance fluorescence, *Nat. Phys.* **5**, 198 (2009).
 - [13] X. Ding, Y. He, Z.-C. Duan, N. Gregersen, M.-C. Chen, S. Unsleber, S. Maier, C. Schneider, M. Kamp, S. Höfling, C.-Y. Lu, and J.-W. Pan, On-demand single photons with high extraction efficiency and near-unity indistinguishability from a resonantly driven quantum dot in a micropillar, *Phys. Rev. Lett.* **116**, 020401 (2016).
 - [14] H. Wang, Z.-C. Duan, Y.-H. Li, S. Chen, J.-P. Li, Y.-M. He, M.-C. Chen, Yu He, X. Ding, C.-Z. Peng, C. Schneider, M. Kamp, S. Höfling, C.-Y. Lu, and J.-W. Pan, Near-transform-limited single photons from an efficient solid-state quantum emitter, *Phys. Rev. Lett.* **116**, 213601 (2016).
 - [15] N. Somaschi, V. Giesz, L. De Santis, J. C. Lored, M. P. Almeida, G. Hornecker, S. L. Portalupi, T. Grange, C. Anton, J. Demory, C. Gomez, I. Sagnes, N. D. Lanzillotti Kimura, A. Lemaitre, A. Auffeves, A. G. White, L. Lanco, and P. Senellart, Near-optimal single-photon sources in the solid state, *Nat. Photonics* **10**, 340 (2016).
 - [16] H. Wang, *et al.*, Towards optimal single-photon sources from polarized microcavities, *Nat. Photonics* **13**, 770 (2019).
 - [17] N. Tömm, A. Javadi, N. O. Antoniadis, D. Najer, M. C. Löbl, A. R. Korsch, R. Schott, S. R. Valentin, A. D. Wieck, A. Ludwig, and R. J. Warburton, A bright and fast source of coherent single photons, *Nat. Nanotechnol.* **16**, 399 (2021).
 - [18] X. Ding, Y.-P. Guo, M.-C. Xu, R.-Z. Liu, G.-Y. Zou, J.-Y. Zhao, Z.-X. Ge, Q.-H. Zhang, H.-L. Liu, L.-J. Wang, M.-C. Chen, H. Wang, Y.-M. He, Y.-H. Huo, C.-Y. Lu, and J.-W. Pan, High-efficiency single-photon source above the loss-tolerant threshold for efficient linear optical quantum computing, *Nat. Photonics* **19**, 387 (2025).
 - [19] H. S. Nguyen, G. Sallen, C. Voisin, P. Roussignol, C. Diederichs, and G. Cassabois, Ultra-coherent single photon source, *Appl. Phys. Lett.* **99**, 261904 (2011).
 - [20] C. Matthiesen, A. N. Vamivakas, and M. Atatüre, Subnatural linewidth single photons from a quantum dot, *Phys. Rev. Lett.* **108**, 093602 (2012).
 - [21] C. Matthiesen, M. Geller, C. H. H. Schulte, C. Le Gall, J. Hansom, Z. Li, M. Hugues, E. Clarke, and M. Atatüre, Phase-locked indistinguishable photons with synthesized waveforms from a solid-state source, *Nat. Commun.* **4**, 1600 (2013).
 - [22] L. Hanschke, L. Schweickert, J. C. L. Carreño, E. Schöll, K. D. Zeuner, T. Lettner, E. Z. Casalengua, M. Reindl, S. F. C. da Silva, R. Trotta, J. J. Finley, A. Rastelli, E. del Valle, F. P. Laussy, V. Zwiller, K. Müller, and K. D. Jöns, Origin of antibunching in resonance fluorescence, *Phys. Rev. Lett.* **125**, 170402 (2020).

- [23] C. L. Phillips, A. J. Brash, D. P. S. McCutcheon, J. Iles-Smith, E. Clarke, B. Royall, M. S. Skolnick, A. M. Fox, and A. Nazir, Photon statistics of filtered resonance fluorescence, *Phys. Rev. Lett.* **125**, 043603 (2020).
- [24] J. C. Lopez Carrero, E. Z. Casalengua, F. P. Laussy, and E. del Valle, Joint subnatural-linewidth and single-photon emission from resonance fluorescence, *Quantum Sci. Technol.* **3**, 045001 (2018).
- [25] A. Gonzalez-Tudela, F. P. Laussy, C. Tejedor, M. J. Hartmann, and E. del Valle, Two-photon spectra of quantum emitters, *New J. Phys.* **15**, 033036 (2013).
- [26] J. Dalibard and S. Reynaud, Correlation signals in resonance fluorescence: Interpretation via photon scattering amplitudes, *J. Phys. France* **44**, 1337 (1983).
- [27] L. Masters, X.-X. Hu, M. Cordier, G. Maron, L. Pache, A. Rauschenbeutel, M. Schemmer, and J. Volz, On the simultaneous scattering of two photons by a single two-level atom, *Nat. Photonics* **17**, 972 (2023).
- [28] A. Aspect, G. Roger, S. Reynaud, J. Dalibard, and C. Cohen-Tannoudji, Time correlations between the two sidebands of the resonance fluorescence triplet, *Phys. Rev. Lett.* **45**, 617 (1980).
- [29] A. Ulhaq, S. Weiler, S. M. Ulrich, R. Roßbach, M. Jetter, and P. Michler, Cascaded single-photon emission from the Molloy triplet sidebands of a quantum dot, *Nat. Photonics* **6**, 238 (2012).
- [30] C. W. Gardiner and M. J. Collett, Input and output in damped quantum systems: Quantum stochastic differential equations and the master equation, *Phys. Rev. A* **31**, 3761 (1985).
- [31] D. F. Walls and G. J. Milburn, *Quantum Optics* (Springer-Verlag, Berlin, 1994).
- [32] M. M. Wang, Y. F. Li, C. Y. Zeng, G. Q. Huang, L. Liu, W. Y. Wang, W. J. Ji, H. Q. Liu, H. Q. Ni, Z. C. Niu, and C. Y. Hu, Converting laser light into single photons with ultralong coherence time, *Optica* **12**, 1838 (2025).
- [33] A. Faraon, I. Fushman, D. Englund, N. Stoltz, P. Petroff, and J. Vučković, Coherent generation of non-classical light on a chip via photon-induced and blockade, *Nat. Phys.* **4**, 859 (2008).
- [34] A. Majumdar, M. Bajcsy, A. Rundquist, and J. Vučković, Loss-enabled sub-Poissonian light generation in a bimodal nanocavity, *Phys. Rev. Lett.* **108**, 183601 (2012).
- [35] J.-T. Shen and S. H. Fan, Strongly correlated two-photon transport in a one-dimensional waveguide coupled to a two-level system, *Phys. Rev. Lett.* **98**, 153003 (2007).
- [36] T. Shi, S. H. Fan, and C. P. Sun, Two-photon transport in a waveguide coupled to a cavity in a two-level system, *Phys. Rev. A* **84**, 063803 (2011).
- [37] D. E. Chang, A. S. Sørensen, E. A. Demler, and M. D. Lukin, A single-photon transistor using nanoscale surface plasmons, *Nat. Phys.* **3**, 807 (2007).
- [38] A. Javadi, *et al.*, Single-photon non-linear optics with a quantum dot in a waveguide, *Nat. Commun.* **6**, 8655 (2015).
- [39] D. Wang, H. Kelkar, D. Martín-Cano, D. Rattenbacher, A. Shkarin, T. Utikal, S. Götzinger, and V. Sandoghdar, Turning a molecule into a coherent two-level quantum system, *Nat. Phys.* **15**, 483 (2019).
- [40] N. O. Antoniadis, N. Tømm, T. Jakubczyk, R. Schott, S. R. Valentin, A. D. Wieck, A. Ludwig, R. J. Warburton, and A. Javadi, A chiral one-dimensional atom using a quantum dot in an open microcavity, *npj Quantum Inf.* **8**, 27 (2022).
- [41] S. K. Liu, O. A. D. Sandberg, M. L. Chan, B. Schirnski, Y. Anyfantaki, R. B. Nielsen, R. G. Larsen, A. Skalkin, Y. Wang, L. Midolo, S. Scholz, A. D. Wieck, A. Ludwig, A. S. Sørensen, A. Tiranov, and P. Lodahl, Violation of Bell inequality by photon scattering on a two-level emitter, *Nat. Phys.* **20**, 1429 (2024).
- [42] N. Tømm, N. O. Antoniadis, M. Janovitch, M. Brunelli, R. Schott, S. R. Valentin, A. D. Wieck, A. Ludwig, P. Potts, A. Javadi, and R. J. Warburton, Realization of a coherent and efficient one-dimensional atom, *Phys. Rev. Lett.* **133**, 083602 (2024).
- [43] J. Wang, X.-L. Zhou, Z.-M. Shen, D.-Y. Huang, S.-J. He, Q.-Y. Huang, Y.-J. Liu, C.-F. Li, and G.-C. Guo, Purcell-enhanced generation of photonic Bell states via the inelastic scattering off single atoms, *Phys. Rev. Lett.* **134**, 053401 (2025).
- [44] Y. J. Lu and Z. Y. Ou, Observation of nonclassical photon statistics due to quantum interference, *Phys. Rev. Lett.* **88**, 023601 (2001).
- [45] A. Kuhlmann, J. Houel, A. Ludwig, L. Greuter, D. Reuter, A. D. Wieck, M. Poggio, and R. J. Warburton, Charge noise and spin noise in a semiconductor quantum device, *Nat. Phys.* **9**, 570 (2013).
- [46] M. M. Wang, Y. F. Li, H. Q. Liu, H. Q. Ni, Z. C. Niu, X. G. Wei, R. F. Yang, and C. Y. Hu, Interference of single photons with ultralong coherence time, *Appl. Phys. Lett.* **125**, 154002 (2024).
- [47] Y. F. Li, M. M. Wang, C. Y. Zeng, H. Q. Liu, H. Q. Ni, Z. C. Niu, and C. Y. Hu, Two-photon interference between an independent laser and single photons with ultralong coherence time, *Phys. Rev. Res.* **7**, 043128 (2025).
- [48] P. Zeng, H. Zhou, W. Wu, and X. F. Ma, Mode-pairing quantum key distribution, *Nat. Commun.* **13**, 3903 (2022).
- [49] Y.-M. Xie, Y.-S. Lu, C.-X. Wen, X.-Y. Cao, Z.-Y. Jia, Y. Bao, Y. Wang, Y. Fu, H.-L. Yin, and Z.-B. Chen, Breaking the rate-loss bound of quantum key distribution with asynchronous two-photon interference, *PRX Quantum* **3**, 020315 (2022).
- [50] H.-T. Zhu, *et al.*, Experimental mode-pairing measurement-device-independent quantum key distribution without global phase locking, *Phys. Rev. Lett.* **130**, 030801 (2023).
- [51] L. Zhou, J. Lin, Y.-M. Xie, Y.-S. Lu, Y. Jing, H.-L. Yin, and Z. Yuan, Experimental quantum communication overcomes the rate-loss limit without global phase tracking, *Phys. Rev. Lett.* **130**, 250801 (2023).
- [52] L. Zhang, W. Li, J. Pan, Y. Lu, W. Li, Z.-P. Li, Y. Huang, X. Ma, F. Xu, and J.-W. Pan, Experimental mode-pairing quantum key distribution surpassing the repeaterless bound, *Phys. Rev. X* **15**, 021037 (2025).
- [53] S.-F. Shao, L. Zhou, J. Lin, M. Minder, C. Ge, Y.-M. Xie, A. Shen, Z. Yan, H.-L. Yin, and Z. Yuan, High-rate measurement-device-independent quantum communication without optical reference light, *Phys. Rev. X* **15**, 021066 (2025).
- [54] M. Zou, *et al.*, Realization of an untrusted intermediate relay architecture using a quantum dot single-photon source, *Nat. Phys.* **21**, 1670 (2025).
- [55] J. R. Johansson, P. D. Nation, and F. Nori, QuTiP 2: A Python framework for the dynamics of open quantum systems, *Comput. Phys. Commun.* **184**, 1234 (2013).
- [56] C. Y. Hu and J. G. Rarity, Extended linear regime of cavity-QED enhanced optical circular birefringence induced by a charged quantum dot, *Phys. Rev. B* **91**, 075304 (2015).